



MOOSE
www.mooseaudio.com

PROUDLY DEVELOPED AND
MANUFACTURED IN PORTUGAL

TL500P

Installation MONO PA amplifier
500W rms toroidal transformer



Presentation:

The Mono channel public address amplifier with a power up to 500W rms. The TL500P features a single channel input performed using a balanced Jack 6.5mm with individual volume control on the real panel. The output signal is available on 2 low impedance outputs in 40Ohm and 80Ohm and 2 high impedance outputs in 75V and 100V using block terminals on the rear panel. It is equipped with an advanced protection circuit which protects against short-circuit and overload when necessary. The TL500 is suited for public address fixed installations where a capable and reliable device is needed, also offering a pre-out (LINK) available to connect another amplifier.


Features:

- High quality PA amplifier
- Installation PA mono amplifier
- 3p XLR signal input and 3p XLR signal output
- RCA REC output and RCA LINK output
- 4-8 ohm & constant-volt. out. (70V and 100V)
- Master volume control on the front panel
- Built-in electronic protection circuitry
- Solid construction for 19" rack - 3U mounting

Technical specifications:

MODEL	TL500P
Type	PA mono power amplifier
Power output (RMS)	500W
Frequency range	50Hz - 14kHz
T.H.D. (20Hz - 20kHz)	< 1% @ 1kHz
S/N Ratio	< 90dB @ 1kHz
Zones	No
Controls	Singal level
indicators	Power on
Inputs	Singal in
Outputs	4ohm, 8ohm, 75V and 100V
Connectors	Input (6.3mm Jack), Link (RCA) & REC (RCA)
Phantom power	No
Other features	Input level adjustment
Protections	Short circuit, thermal overload
Operating voltage	230V AC (factory config.), 50-60Hz
Power consumption	500VA
Cooling	Continuously speed fan, 120mm / 230V AC
Dimensions (WxDxH)	4RU spaces, 360mm depth
Weight	20Kg

Other pictures:



Rear panel

